HDMI Video up to 1080p

**HDCP** compliant

QuickSwitch! button for easy switching by a mere flip!

Switching Software Client for Windows & Mac included!!

Software hotkeys & Universal Hotkeys both available!!!

2 x USB 2.0 Hub Ports for keyboard, mouse or high-speed USB devices!!!!

# **UHV-TA2**

# 2-port HDMI USB Cable KVM Switch w/ Audio & Mic

1 x 1.5M Wired QuickSwitch! button for instant desktop switching 2 x 0.9M fixed KVM .& Audio/Mic Combo Cables (2 x USB)

The UHV-TA2 is a 2-port compact HDMI USB "Cable KVM Switch" with 2 sets of fixed KVM cables and a wired QuickSwitch! button for easy connection to your two computers. It allows you to access, control, boot and reboot two HDMI and USB-enabled *multimedia* computers with only one USB keyboard, mouse, HDMI-enabled multimedia display and an extra set of speakers. For easy and fast switching between two computers, you can use either keyboard hotkeys, the QuickSwitch! button or the Switching Software Client installed on your PCs!

## QuickSwitch! button for instant switching operation

The QuickSwitch! button can be conveniently placed near your hand on the desktop. Whenever you need to switch computer channel, you can press it lightly for instant switching to the other computer. It is the most easy and fastest way to switch. Beside the QuickSwitch! button, you can also use the keyboard hotkeys and software switching utility.

### **Switching Software Support for PC and Mac**

The UHV-TA2 comes with both Windows and Mac version of the Switching Software utility program that can be installed on the connected computers to facilitate easy "software" switching. The Switching Software can show you the current active PC, and allows you to select PC as well as configure keyboard hotkeys. It appears as an icon on the system tray of your Window desktop, and will change its number icon upon switching to show the active computer port. With this software utility, it will give KVM users utmost convenience and control.

(Product Photo - TBD)

UHV-TA2 2-port Compact HDMI USB Cable KVM Switch w/ Audio, Mic and QuickSwitch! button

#### USB 2.0 hub ports compliant for USB keyboard, mouse and high-speed device sharing

The USB 2.0 interface offers multi-platform support for PC and Macintosh. The two USB 2.0 keyboard and mouse ports are actually transparent USB hub ports that feature a full driver support for advanced keyboard/mouse functionalities. In addition to the usual connections of a set of USB keyboard and mouse, the two USB 2.0 keyboard & mouse ports can also be connected to high-speed USB devices such as USB disk storage or webcam, etc.

#### **HDMI and HDCP compliant for High-Definition video enjoyment**

This HDMI USB KVM Switch supports resolution up to Full HD 1080p. It also supports HDCP (High-bandwidth Digital Contents Protection).

#### Multi-channel audio support

The HDMI interface has integrated multi-channel audio within so that users can enjoy high-definition sound that comes from a single HDMI cable. It allows you to leverage the multimedia systems on each of your two HDMI-enabled computers. You can monitor the audio input of each computer for maximum convenience.

#### Audio and Microphone Switching offers uninterrupted multimedia experience

The audio and microphone switching function of UHV-TA2 allows you to leverage the multimedia systems on each of your two computers. User can choose to use either independent/simultaneous switching of both PC channel and

audio/microphone channel for their maximum convenience. Furthermore, it offers you a user-programmable simultaneous/independent switching option between PC and audio/mic channel switching.

### Zero Cabling Hassles for KVM users

The HDMI USB Cable KVM Switch saves you cabling troubles with its 2 x fixed KVM and audio/mic cables (USB + USB), so that you don't have to worry about finding suitable cables to fit—It's already attached with the KVM switch body in one piece!

#### **Features**

- 2-port HDMI USB Cable KVM Switch with 2 x fixed KVM & Audio/Mic Combo Cables
- 1 x fixed wired (1.5M) QuickSwitch! button for instant toggling between two computers
- 2 x fixed (0.9M) HDMI USB KVM audio/mic Combo cables
- Windows and Mac version of Switching Software Utility for easy switching
- USB 2.0 hub ports for keyboard, mouse or other high-speed USB devices
- HDMI Digital Video up to 1080p
- Audio and Microphone switching for uninterrupted multimedia experience across multi-platforms
- Configurable independent/simultaneous switching of both PC and audio/mic channel
- Multi-platform support for PC and Macintosh platforms
- Hot-plugging PCs for maintenance without powering down the KVM Switch or PCs
- User definable hotkeys and universal hotkey for PC switching
- 3 modes of Channel selection either by QuickSwitch! button, keyboard hotkeys or Switching Software
- LED indicators for easy status monitoring
- USB interface power

#### **Specifications**

Model No.	UHV-TA2
PC Connections	2
<b>Console Connections</b>	1
Cables	Fixed 2 x USB HDMI KVM & Audio/Mic
	Combo Cables
PC Port Connectors	2 x USB Type A
	2 x HDMI
	2 x 3.5mm audio plug
	2 x 3.5mm mic plug
Console Port Connectors	2 x USB 2.0 Type A (Keyboard & Mouse / High-
	speed USB devices)
	1x HDMI
	1 x 3.5mm audio jack
	1 x 3.5mm mic jack
KVM Cables	2 x fixed 0.9M HDMI USB KVM & audio/mic
	combo cable
QuickSwitch button	1 x 1.5M QuickSwitch! Button for instant
	switching
PC selection	QuickSwitch! button/Hotkeys/Switching
	Software
PC port LED	2 x Green
Video resolution	HDMI – 1080p
Power Type	USB interface power
Size	Cable KVM
Dimensions (L x W x H)	38 x 20 x 11mm
Housing	Plastic
Safety / Emission	FCC, CE
Salety / Ellission	100,02