
DATASHEET

FTTH Box for 4 adapters SC-S or LC-D 80x80 with cable guide, shrinkversion









General data

- Suitable for drop cable to splice inside the box with pigtail inside
- Capable for the installation of different length of pre-terminated drop cable with LC and SC connectors, no splice process will be needed in this application
- The box is capable for 1/2/4F SC connections or 2/4F LC connections
- **It can be Din rail mounted or wall mounted with screw**
- The splice cassette is designed for 0.9mm buffer splice(40*1.2mm
- sleeves), bare fiber splice (40*0.5mm sleeves) or crimp splice
- It’s capable for drop cable between 2.0mm~5.0mm

Technical properties

Cable entry without cable gland	5 x 5 mm

This datasheet was created automatically on 04-11-2026 . Technical changes reserved.

EFB-Elektronik GmbH
Striegauer Straße 1
33719 Bielefeld

fon: +49 521 40 41 8-0
fax: +49 521 40 41 8-50

info@efb-elektronik.de
www.efb-elektronik.de

WIR SORGEN FÜR VERBINDUNG
WE CARE FOR CONNECTION

DATASHEET

FTTH Box for 4 adapters SC-S or LC-D 80x80 with cable guide, shrinkversion

Cable sheath support	True
Colour	white
Dimensions	80 x 80 x 28 mm
Foreign body and contact protection	Protection against medium-sized foreign bodies
Hinged splice cassette	True
Holder for gas blocker	False
IP Protection	IP20
Material	Plastic
Max. Assembly (Adapter)	4
Mounting method	Wall mounting
Number of Fibres	4
Operating Temperature	0 – 50 °C
Possibility of mast mounting	False
Scope of application	Indoor
Suitable for adapter	SC Simplex/LC Duplex/E2000®
Type of Splice protection	Crimp or Thermo
Water protection	Without protection
With Fiber overlength cassette	True

Available variants

ArtNr.	Bezeichnung	Access Control
FTTH-BOX-IN-6	FTTH Box for 4 adapters SC-S or LC-D 80x80 with cable guide, crimpversion	Without
FTTH-BOX-IN-7	FTTH Box for 4 adapters SC-S or LC-D 80x80 with cable guide, shrinkversion	Without

Note on Intended Use

This data sheet is intended solely to describe the technical characteristics of the product. It does not replace an assessment of the product's suitability for a specific application. The user is responsible for ensuring that the product is used in accordance with its technical specifications and applicable legal and regulatory requirements.

EFB-Elektronik GmbH
Striegauer Straße 1
33719 Bielefeld

fon: +49 521 40 41 8-0
fax: +49 521 40 41 8-50

info@efb-elektronik.de
www.efb-elektronik.de

WIR SORGEN FÜR VERBINDUNG
WE CARE FOR CONNECTION